

ClearOne WS800 Digital Wireless Microphone System Preset Configurations

	Parameter	Range	Small Conference System (1 - 16 Channels) Large Conference System (17 - 32 Channels)
Global Parameters	Frequency Response	Conference	Conference
	AC Power Plug	USA	USA
	RF Frequency Band	902-928 MHz	902-928 MHz
Receivers	Audio Connectors	Euroblocks	Euroblocks
	Channel Output Level	-50 to 0 dB	0 dB
	Mute Output level	-50 to 0 dB	0 dB
	Channel Out Mute		Off
	Headphone Out Mute	On/Off	Off
	Channel Name	10 Alphanumeric	Slot 1, Slot 2 etc
	RF Channel	1-32 Conference	Maximum Spacing
	Cntrl Buttons Locked	On, Off	On
ClearOne Remote Tabs:	Rack Name	1 to 8 racks	Receiver Serial Number
Tab: Settings	Antenna Phantom Power	On / Off	On
Tab: Settings	Redundancy	On / Off	Off
Tab: Settings	1/4" Mixed Audio Output	Headphone / Balanced Line Out	Headphone
Tab: Preset	Load	Load or Save	Small Conference or Large Conference
Tab: GPIO	Load	Load Preset, Xmitter Button Press,etc	None
Tab: Security	Password	8 Alphanumeric Characters	None
Tab: Alerts	Alerts	Low Bat, Old Bat, Fault	None
Front-Panel	1/4" Volumn Pot	off to max	Off
Transmitters	Channel Pre-set	Pre-set 1	
	Conf. 1-15		1,3,5,7,9,11,13,15
	Conf. 2-16		2,4,6,8,10,12,14,16
	Conf. 17-31		17,19,21,23,25,27,29,31
	Conf. 18-32		18,20,22,24,26,28,30,32
Belt-packs	Channel Number		Match Receiver
	Name	10 Characters Alpa-Numeric	Slot 1, Slot 2, etc
	Mic Pad	+20 to -10 dB	0dB
	Transmit Power	1 mW, 10 mW, 25, mW, 50 mW	1 mW
	Switch	On/Off; On/Mute; On/Logic Mute;	On / Off
	75 Hz Roll Off	On/Off	On
	Cntrl Buttons Locked	On / Off	On
Hand-Helds	Channel Number		Match Receiver
	Name	10 Characters Alpa-Numeric	Slot 1, Slot 2, etc
	Mic Pad	+20 to -10 dB	0dB
	Transmit Power	1 mW, 10 mW, 25, mW, 50 mW	1 mW
	Switch	On/ON	On / Off
	Roll Off	No roll off, 75Hz Roll Off	On
	75 Hz Roll Off	On/Off	On
Cntrl Buttons Locked	On / Off	On	
	Capsule	H18	H18
Podium Goosenecks	Channel Number		Match Receiver
	Name	10 Characters Alpa-Numeric	Slot 1, Slot 2, etc
	Mic Pad	+20 to -10 dB	0dB
	Transmit Power	1 mW, 10 mW, 25, mW, 50 mW	1 mW
	Switch	On/ON	On / Off
	75 Hz Roll Off	On/Off	On
	Capsule	Cardiod, Omni	As ordered
	Gooseneck Lengths	12", 18"	As ordered
	Button	Toggle On Off, Press toTalk, Press to Mute	Toggle On/Off
Table-Top Boundary	Channel Number		Match Receiver
	Name	10 Characters Alpa-Numeric	Slot 1, Slot 2, etc
	Mic Pad	+20 to -10 dB	0dB
	Transmit Power	1 mW, 10 mW, 25, mW, 50 mW	1 mW
	Switch	On/ON	On / Off
	75 Hz Roll Off	On/Off	On
	Capsule	Cardiod, Omni	As ordered
	Button	Toggle On Off, Press toTalk, Press to Mute	Toggle On/Off