

# LS6WT WALL SPEAKER



These wall mount speakers provide high quality and high fidelity audio reproduction for realistic conferencing and voice lift experiences. The modern styling enhances any professional setting.

## Specifications

**Frequency Range**

- 70 Hz - 20 kHz

**Power Rating**

- 40 W

**Sensitivity (1W/1M)**

- 90 dB

**Impedance**

- 8 Ohm

**Dispersion Angle**

- 90 degrees

**Woofers**

- 1 x 6 inch

**Tweeter**

- 1 x 1 inch

**Enclosure Material and Finish**

- ABS, Black

**Dimensions**

- 11.12 x 8.46 x 7.48 in  
( 284 x 215 x 190 mm)

**Part Number**

- 910-151-002-01-1



Delivers professional audio in classroom settings.



Provides room-filling sound for medium-sized meeting rooms.



Pairs with BMA CT or BMA 360 for large meeting spaces.

## Installation

### Required Tools and Parts


- Pencil
- Screwdriver
- Screws (2)
- Drill
- Anchors, if mounting to drywall
- Hammer, if mounting to drywall



#### Caution!

- Install in accordance with all applicable local codes.
- Before you start, ensure that power to the amplifier is off.

### 1. Attach the Mounting Bracket to Structure



- a. Determine where the speaker is to be mounted and whether it is to be mounted vertically or horizontally.
- b. Unscrew the Fastener thumbscrews on either sides of the speaker to remove the U-bracket.
- c. Using the U-bracket as a template, mark the three holes in the wall with a pencil.
- d. Drill the appropriate size holes for the screws or anchors as necessary depending on the mounting surface being used (wood, drywall, etc.)
- e. If mounting in drywall, use the hammer and carefully tap an anchor into each of the drilled holes.
- f. Line the U-bracket up with the holes and screw it in place.

### 2. Attach Wires to the Speaker



- a. Loosen the two speaker wire input post screws on the back of the speaker.
- b. Connect the wires from the power amplifier to the terminal connections on the back of the speaker as follows:
  - Positive signal to **red** connector
  - Negative signal to black connector
- c. Carefully and securely tighten each of the post screws.

### 3. Attach the Speaker to the Mounting Bracket



- a. Position the speaker so the speaker mounting holes line up with the two U-bracket fastener holes.
- b. Insert each of the thumbscrew fasteners through the bracket mounting holes and tighten to secure speaker to U-bracket.



**Caution:** Do **not over-tighten** screws.

## SALES AND INQUIRIES

#### Headquarters

5225 Wiley Post Way  
Suite 500  
Salt Lake City, UT 84116

#### US & Canada

Tel: +1.801.975.7200  
[global@clearone.com](mailto:global@clearone.com)

#### International

Tel: +1.801.975.7200  
[global@clearone.com](mailto:global@clearone.com)

#### Sales

Tel: +1.801.975.7200  
[sales@clearone.com](mailto:sales@clearone.com)

#### Tech Support

Tel: +1.801.974.3760  
[audiotechsupport@clearone.com](mailto:audiotechsupport@clearone.com)