

CHAT® 150 | CHATAttach™ 150 USB

Personal/Group Speaker Phones

Speaker phones for individual, small, medium or large group use. The CHAT 150 and CHATAttach 150 USB connect to PCs for rich, full-duplex audio communications and can be used with VoIP softphones, Web collaboration, instant messaging and any other applications requiring two-way audio. A perfect addition to the office or conference room for greatly enhanced collaboration.

ClearOne



DELIVERS
SUPERIOR
HANDS-FREE
AUDIO FOR
PC-BASED
COLLABORATION
APPLICATIONS

APPLICATIONS

- Web Conferencing
 - + IBM Workplace
 - + Microsoft Live Meeting, WebEx
- VoIP Softphones
 - + Avaya, Cisco, Nortel, Mirial
- Internet Telephony
 - + Google Talk, Skype, Vonage
- Instant Messenger
 - + AOL, Microsoft MSN, Yahoo

ADVANTAGES

- Enable full-duplex speaker phone capabilities on PCs or laptops
 - + Connect the CHAT 150 or the CHATAttach 150 to laptops & PCs via USB for hands-free audio for:
 - > VoIP softphones
 - > Instant Messaging audio chats
 - > Web conferences
- Enjoy rich audio playback
 - + Full bandwidth frequency response provides rich audio playback with media players
- Enjoy crisp, clear audio
 - + Advanced ClearOne HDConference™ audio processing technologies deliver remarkably rich, full audio for natural, effortless conversations:
 - > True full duplex performance allows user to listen and speak at the same time without audio cutting in and out
 - > Distributed Echo Cancellation®
 - > Noise cancellation
 - > Advanced automatic level management
- + Three built-in microphones provide full 360-degree coverage up to 8 feet from device
- + Bridge audio from PC applications with audio on telephone for instant 3-way conference bridge

HDConference™

> **CHAT 150 COMPONENTS**



CHAT 150 Unit
Part # 910-156-200



USB 2.0 Connection Cable
Part # 830-156-200



Quick Start Guide
Part # 800-156-202

> **CHATAttach 150 COMPONENTS**

CHATAttach Packout for the CHAT 150



Two CHAT 150 Units
Part # 910-156-200



USB 2.0 Connection Cable
Part # 830-156-200



CHATAttach Cable
Part # 830-156-010L



CHATAttach Power Supply
Part # 551-156-200



CHATAttach Quick Start Guide
Part # 800-156-225

Ready out of the box

All the components you need to quickly get up and running, including cabling and Quick Start Guide.

CHATAttach Expansion Cable Packout



CHATAttach Cable
Part # 830-156-010L




CHATAttach Power Supply
Part # 551-156-200




CHATAttach Quick Start Guide
Part # 800-156-225

> **ROOM APPLICATIONS**

CHAT 150



CHATAttach 150



Configuration Software

Allows users to easily switch between devices; software applies optimized settings to CHAT 150 for each device. Auto-updates from the Web to keep software & CHAT 150 up-to-date with the latest enhancements.

> **SPECIFICATIONS**

Connections

USB Connector
Version 2.0 Compatible
Type: Mini B Female

Keyed Connector
Keyed RJ-45 (8 Conductor)

Controls

Volume Up
Volume Down
Microphone Mute

Operating System Support

Windows XP
Windows Vista
Windows 7

Audio

Speaker
Bandwidth: 190 Hz - 20 kHz
Max Output Level: 85 dB SPL @ 1 meter

Microphone
Bandwidth: 100 Hz - 12 kHz

Power

USB-powered
5 VDC @ 500 mA Maximum

External Power Supply
100 - 240 VAC Input
9 VDC @ 560 mA Output

Environmental

Operating temperature:
5 - 40° C (41 - 104° F)

Mechanical

CHAT 150 Dimensions (W x D x H):
7.4" x 7.4" x 1.8"
(18.8 cm x 18.8 cm x 4.6 cm)

CHAT 150 Weight:
1.17 lbs (0.53 kg)

Compliance

RoHS
FCC Class A Part 15
FCC Part 15.19 (A) (3)
ICES-003
EU Compliance

Model Numbers

910-156-200
Chat 150 USB

- Single CHAT 150 and Connecting Cable

910-156-200-00
CHATAttach 150

- Two (2) CHAT 150 Devices, Connecting Cables and Power Supply

910-156-222

CHAT 150 Avaya

- CHAT 150 and Connecting Cable to Avaya Enterprise Phone

910-156-230

CHAT 150 VC

- CHAT 150 and Cable to Video Conference System

Accessory Part Numbers

860-156-230L

CHAT 150 VC Accessory Kit

- Includes Video Conferencing Breakout Box, Power Adapter, International Power Clips, RCA Connection Cable, 25' Link Cable

860-156-222L

CHAT 150 Avaya Accessory Kit

- Includes Breakout Box for 2410, 2420, 4610 and 4621 Telephone Handsets, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable

860-156-220L

Chat 150 Cisco Accessory Kit

- Includes Breakout Box for 7940, 7960, and 7970 Telephones, Power Adapter, International Power Clips, RJ-9/RJ-9 Telephone Cable, 25' Link Cable

910-156-225

CHATAttach Expansion Kit

- Includes Cables, Power Supply and Quick Start Guide to Update Two (2) CHAT 150 Devices to CHATAttach

> **CLEARONE LOCATIONS**

Headquarters:

Salt Lake City, UT USA

5225 Wiley Post Way
Suite 500

Salt Lake City, UT 84116

Tel: 801-975-7200

Toll Free: 800-945-7730

Fax: 801-977-0087

e-mail: sales@clearone.com

Latin America

Tel: 801-974-3621

e-mail: global@clearone.com

EMEA

Tel: 44 (0) 1189 036 053

e-mail: global@clearone.com

APAC

Tel: 801-303-3388

e-mail: global@clearone.com

Technical Support

APAC

Tel: 801-283-5936

e-mail: tech.support@clearone.com